



RAXPZ400 - RAXNPZ 400

# Combined Bearings with incorporated thrust plate

型号	F <sub>w</sub>		D		C		Da	C <sub>1</sub>		C <sub>2</sub>	rS <sub>min</sub>
		mm		mm		mm	mm		mm	mm	mm
RAXPZ 410	10	+0.022 +0.013	19	0 -0.009	21	0 -0.12	22.4	7	+0.05 -0.06	6	0.35
RAXPZ 412	12	+0.027 +0.016	21	0 -0.009	21	0 -0.12	26.4	7	+0.05 -0.06	6	0.35
RAXPZ 415	15	+0.027 +0.016	24	0 -0.009	21	0 -0.12	28.4	7	+0.05 -0.06	6	0.35
RAXPZ 417	17	+0.027 +0.016	26	0 -0.009	23	0 -0.12	30.4	7	+0.05 -0.06	8	0.65
RAXPZ 420	20	+0.033 +0.020	30	0 -0.009	27	0 -0.12	35.4	9	+0.05 -0.06	9	0.85
RAXPZ 425	25	+0.033 +0.020	37	0 -0.011	27	0 -0.12	43.0	9	+0.05 -0.06	9	0.85
RAXPZ 430	30	+0.033 +0.020	42	0 -0.011	27	0 -0.12	48.0	9	+0.05 -0.06	9	0.85
RAXPZ 435	35	+0.041 +0.025	47	0 -0.011	27	0 -0.12	54.0	9	+0.05 -0.06	9	0.85
RAXPZ 440	40	+0.041 +0.025	52	0 -0.013	27	0 -0.12	61.0	9	+0.05 -0.06	9	0.85
RAXPZ 445	45	+0.041 +0.025	58	0 -0.013	27	0 -0.12	66.0	9	+0.05 -0.06	9	0.85
RAXPZ 450	50	+0.041 +0.025	62	0 -0.013	30	0 -0.12	71.0	9	+0.05 -0.06	11	1.30
RAXPZ 460	60	+0.049 +0.030	72	0 -0.013	32	0 -0.12	86.0	11	+0.05 -0.06	11	1.30
RAXPZ 470	70	+0.049 +0.030	85	0 -0.013	32	0 -0.12	96.0	11	+0.05 -0.06	11	1.30